

PROVERO

Instrukcja obsługi czujnika zmierzchu ID-0054


ZASTOSOWANIE:

Produkt może automatycznie włączać lub wyłączać światło w zależności od oświetlenia otoczenia. Temperatura i wilgotność otoczenia nie mają na to wpływu. Jest nie tylko wygodny, ale i praktyczny.

Służy do oświetlenia drogowego, oświetlenia ogrodowego itp.

DANE TECHNICZNE:

- Źródło zasilania: 220-240V/AC;
- I max.: 15 A;
- P. max.: 3500 W;
- Częstotliwość zasilania: 50/60Hz;
- Światło otoczenia: <2-100 LUX;
- Temperatura pracy: -20 ~ +40 °C;
- Wilgotność pracy: <93% RH



Rys. nr 1

WARUNKI BEZPIECZEŃSTWA I MONTAŻU:

- Wyłączyć zasilanie, zgodnie z właściwym miejscem instalacji,
- Zainstalować produkt za pomocą dołączonych śrub (Rys. nr 1).
- Połączyć przewód z produktem zgodnie ze schematem połączeń (Rys. nr2).
- Przesunąć pokrętło LUX na pozycję księżycy i włączyć zasilanie.

Kiedy testujesz w ciągu dnia.

Powinieneś przykryć produkt czarną, nieprzezroczystą szmatką. Gdy tkanina pokrywa okno wykrywania fotokomórki, światło otoczenia fotokomórki jest mniejsze niż 2 luksy, lampa będzie włączona.

Gdy zdejmiesz tę szmatkę, lampa wyłączy się automatycznie. Po przesunięciu pokrętła LUX do pozycji słońca lampa może świecić w świetle otoczenia mniejszym niż 100 LUX.

INFORMACJE DODATKOWE

- Przed fotokomórką nie powinna znajdować się żadna przeszkoda wpływająca na akceptację światła naturalnego;
- Przed fotokomórką nie powinien znajdować się obiekt kołyszący się.
- Nie instaluj fotokomórki pod światłem lub w miejscu, w którym światło będzie padało na fotokomórkę.

IMPORTER: IDEA LED Spółka z o.o.
Masłów Pierwszy, ul. Jana Pniążka 6a26-001 Masłów
www.ideal.ed.eu



Oznakowanie umieszczone wskazuje na konieczność selektywnego zbierania zużytego sprzętu elektrycznego i elektronicznego. Wyrobów tak oznakowanych, pod karą grzywny, nie można wyrzucać do zwykłych śmieci razem z innymi odpadami. Wyroby takie mogą być szczególnie dla środowiska i zdrowia ludzkiego, wymagają specjalnej formy przetwarzania, w szczególności odzysku, recyklingu lub unieszkodliwiania. Wyroby tak oznakowane powinny zostać oddane do punktu zbierania zużytego sprzętu elektrycznego i elektronicznego. Informacje na temat punktów zbierania/odzysku udzielają władze lokalne lub sprzedawcy tego rodzaju sprzętu. Zużyty sprzęt może zostać również oddany do sprzedawcy, w przypadku zakupu nowego wyrobu w ilości nie większej niż nowy kupowany sprzęt tego samego rodzaju. Powyższe zasady dotyczą obszaru Unii Europejskiej. W przypadku innych państw, należy stosować prawne regulacje obowiązujące w danym kraju. Zalecamy kontakt z dystrybutorem naszego wyrobu na danym obszarze.

PROVERO


Instruction - Light-Control Sensor ID-0054

TO USE:

The product can turn on or turn off light automatically according to ambient light. Ambient temperature and humidity can't affect it. It is not only convenient but also practical; it can control the load working only at night. It is used for road light, garden light etc.

SPECIFICATION:

- Power source: 220-240V/AC
- Rated Current: 15A
- P. max.: 3500 W;
- Power Frequency: 50/60Hz
- Ambient Light: <2-100LUX (adjustable)
- Working Temperature: -20~+40°C
- Working Humidity: <93%RH



#1

SAFETY AND INSTALLATION CONDITIONS:

- Switch off the power. According to the correct installation place
- Install the product with the enclosed inflated screws. (See drawing #1).
- Connect the wire with the product as per the connection-wire diagram. (See drawing #2)
- Slide the LUX knob to position moon and switch on the power.

When you test in daytime. You should cover a black opaque cloth on the product.

When the cloth mantles the detection window of the photocell, the ambient light of the photocell is less than 2 LUX, the lamp will be on. When you take off this cloth, the lamp will be off automatically. When you slide the LUX knob to position sun, the lamp could be on in the ambient light less than 100LUX.



#2

NOTE:

- In front of the photocell, it should be no obstruction affecting to accept natural light;
- In front of the photocell, it should be no swaying object.
- Don't install the photocell under the light or in the place where the light will be irradiated to the photocell.

IMPORTER: IDEA LED Spółka z o.o.
Masłów Pierwszy, ul. Jana Pniążka 6a26-001 Masłów
www.ideal.ed.eu



The symbol shown indicates that used electrical and electronic equipment must be collected separately. Products bearing this symbol must not be disposed of in regular trash along with other waste, under penalty of a fine. Such products may be harmful to the environment and human health and require special treatment, in particular recovery, recycling, and/or disposal. Products bearing this symbol should be taken to a collection point for waste electrical and electronic equipment. Information on collection points is available from local authorities or retailers of such equipment. Waste equipment may also be returned to the retailer when purchasing a new product, provided the quantity does not exceed that of the new equipment of the same type being purchased. The above rules apply within the European Union. For other countries, the legal regulations in force in the respective country must be followed. We recommend contacting the distributor of our product in your area.