

# PROVERO

## TOUCHLESS SWITCH

### ID-0205/ID-0206

#### DESCRIPTION:

The contactless switch activates the electric circuit at the moment motion registration e.g. a swipe of a hand from a distance of up to 8 cm.

The device is used to illuminate mirrors, cabinets, drawers, etc.

#### TECHNICAL DATE:

Operating voltage:12-24V DC

Switching power:60W(dla 12V), 100W(dla 24V)


Output current:5A(dla 12V), 4A(dla 24V)

IP rating:IP20

Application:inside

Cable length:150cm i 15cm

Operating range:8cm



#### SAFETY AND INSTALLATION CONDITIONS:

1. Read these instructions carefully before assembly.
2. The device is intended for indoor use especially, for LED lighting systems.
3. When connecting the device to the system, you must not, under any circumstances, exceed the permissible technical parameters stated in the specifications.
4. Turn off the power.
5. Mark the mounting spot where the device is to be installed and run the wire through it.
6. The wires marked 'input' should be connected to a power source with a voltage of 12 - 24V. The wires marked 'output' should be connected to the powered LED lamps.
7. Before turning on the power, verify the validity of the LED installation.
8. Connect using a JSTm socket and plug (if there is no JSTm socket at the LED strip or power supply, buy a proper socket).
9. Clean with soft and dry fabrics.

